



1. Remove (10) #10-32x1 ¼ doorframe fasteners.
2. Remove doorframe and lens assembly.
3. Remove (4) #10-32 hex nuts from the reflector.
4. Remove reflector.
5. Make electrical connections to fixture.
6. Secure fixture to ceiling/wall using the fixture mounting holes. There are 6 holes on each side, 12 total. 3/8" diameter holes are provided, mounting hardware supplied by others.

**Then reverse steps for re-install of reflector/doorframe lens assembly.**